

1.5μm (6+1) x1 Pump and PM Signal Combiner

Key Features

- High Power Transfer Efficiency
- Low signal insertion loss
- High PER
- High power package
- Freely selectable signal and pump wavelength
- Custom Configurations Available

Applications

- Pumping of fiber laser and amplifier
- Pumping of multi-core and large mode area fibers (LMA)
- Pump combiner for Nd-, Yb-, Er-, Ho-, Tm-fiber
- Industrial, Biomedical, Telecommunication
- Metrology, Life Science, Imaging, Quantum optics
- Gravitational wave detection, Atom cooling and trapping

DK Photonics' (6+1) x1 Multimode Pump and PM Signal Combiner is designed for high power applications. It features exceptional optical characteristics. These devices can combine N pump lasers and 1 signal channel into one fiber and create a high-power pump laser source, delivering the combined power for applications in industrial, military, medical and telecommunications markets. It has a heat sink package and a hole for temperature monitoring.

DK Photonics' Multimode Pump and PM Signal Combiners offer efficient power transfer for high power applications like direct diode materials processing and pump cascading with a maximum conservation of brightness. The Multimode Combiners can be designed to meet a wide range of power handling configurations, number of input fibers and adaptation to different fiber types.



Performance Specifications (Typical Configuration)

Parameters	Values
Signal Operating Wavelengths	1530-1575nm
Pump Operating Wavelengths	780-1000nm
Number of Multimode Inputs	6
Number of Signal Ports	1
Number of Output Ports	1
Pump Input Fiber	105/125μm, NA0.22
Signal Input Fiber	PM12/130μm, NA0.20/0.46
Output Fiber	PM25/300μm, NA0.09/0.46
Min. Pump Efficiency	95%
Max. Signal Insertion Loss	0.70dB
Min. Polarization Extinction Ratio	17 dB
Power per Multimode Input	100W
Optical Return Loss - Pumps	>35dB
Optical Isolation	>20dB
Max. M ²	1.3
Operating Temperature	0~75°C
Storage Temperature	-40~85°C

Remark:

* Other configuration and higher power handling can be customized.

* Other pump fibers 106.5/125μm, NA0.22, or 135/155μm, NA0.22 can be customized.

* All combiners default with bare fiber, 0.8m length of pigtail, please contact us for special request.

For more Info

Please contact us at:

Tel: +86-755-23736280

Fax: +86-755-26746512

E-mail: sales@dkphotonics.com

<https://www.dkphotonics.com>

Add.:

4F, Bldg. 18, Qinghu Industrial Park,

Dahe Road, Longhua Dis.,

Shenzhen, China 518109



1.5μm (6+1) x1 Pump and PM Signal Combiner

General Configuration:

Type	Signal Wave-length(nm)	Pump fiber	Input signal fiber	Output fiber	Max. Signal IL	Min. PER (dB)	Max. Pump Effi.	Max. Power Handling
(6+1) ×1	1530-1575	105/125 0.22	PM1550-XP	PM-GDF-1550	0.7dB	18dB	90%	25W/leg
(6+1) ×1	1530-1575	105/125 0.22	PM-GDF-1550	PM-GDF-1550	0.7dB	18dB	90%	25W/leg
(6+1) ×1	1530-1575	105/125 0.22	PM12/130 DC	PM12/130 DC	0.7dB	18dB	90%	50W/leg
(6+1) ×1	1530-1575	105/125 0.22	PM12/130 DC	PM25/300 DC	0.7dB	16dB	95%	100W/leg

Remark:

- * Other configuration and higher power handling can be customized.
- * Other pump fibers 106.5/125μm, NA0.22, or 135/155μm, NA0.22 can be customized.
- * All combiners default with bare fiber, 0.8m length of pigtail, please contacts us for special request.

Package Information:

Package Type	P2	P3	P4
Dimensions (mm)	65x12x7	80x12x8	100x15x10

*Due to ongoing design improvements, the package size is subject to change. According to the different configuration, power handling, and fiber core diameter, we will choose the appropriate package size. Please contact DK Photonics for confirmation.

*High power device package must be mounted onto heat sink (active cooling is suggested) with thermal paste.

Order information P/N: PMPSC-A-B-C-D-E-F-G-H

When you inquire, please provide the correct P/N number according to our ordering information, and attach the appropriate description would be better. If need any connector, we do not recommend choosing a 250μm bare fiber pigtail.

A	B	C	D	E	F	G	H
Port	Pump Type	Signal Wavelength	Power per Multi-mode Input	Pump Fiber	Signal Fiber	Output Fiber	Fiber length
61: (6+1) X1	F: Forward pump B: Backward pump	15:1550nm	10:10W 25:25W 50:50W XX: Other	XXX (fiber code)	XXX (fiber code)	XXX (fiber code)	08:0.8m(default) 10:1.0m

Part Number Example: PMPSC-61-F-15-20-105/125/22-P15X-P12/130/20D-08

Description: (6+ 1) x 1 Pump and PM Signal Combiner, Forward pump, 1550nm signal wavelength,20W per pump power, 105/125μm,0.22NA input pump fiber, PM1550-XP input signal fiber, PM12/130um, NA0.20/0.46 output fiber, 0.8m fiber length.

Ordering Information for Custom Parts

If you need to customize other specifications, please provide detailed description for your requirement.